



MULTIMETRI



MI 7053



MI 7006



MI 7035

TIP	MI 7051	MI 7053	MI 7006	MI 7035
Napon	100mV ...1000V	5V ...1500V	10mV ...650V	3V ...600V
Struja	0,1A ...5A	0,5A ...15A	10μA ...30A	0,3A ...30A
Karakteristični otpor	4MΩ	2,2MΩ	10 MΩ	2,2 kΩ/V
Broj mernih dometa	23	20	61	21
Ohmski otpor	100, 1k, 5k,	15, 150, 1,5k, 150k, (2Ω)	1,10,100, kx1,10,100	1,10,100
Pojačanje dB	-	-	∞	-
Indikacija polariteta	-	-	+, -, ~	-
Redosled faza	-	-	-	RST
Klasa tačnosti	2,5 ≅	2,5 ≅	1,5 = 2,5 ~	2,5 ≅
Značilnosti	Tonski davač	Tonski davač	Avto. Polariteta	-
Napajanje	1 x 9 V 6F22	1 x 9 V 6F22	6 x1,5 V R6	2 x 1,5 V R6
Dimenzije (mm)	102 x 142 x 40	102 x 142 x 40	100 x 165 x 65	100 x 165 + 16 x 61

Pribor:

- Plastični etui za tip MI 7035.
- Merne veze
- Zaštita od gume za tipe MI 7051, MI 7053.



MULTIMETRI



MI 7042



MI 7043



MI 7045

TIP	MI 7042	MI 7043	MI 7045	MI 7046
Napon =	100mV ...1000V	100mV ...1000V	120mV ...1000V	100mV ...1000V
~	3V ... 1000V	3V ... 1000V	3V ... 1000V	10V ... 1000V
Struja =	20μA ...3A	50μA ...5A	240μA ...30A	50μA ...1A
~	1mA ...3A	1mA ...10A	60mA ...30A	3mA ...3A
Karakteristični =	50 kΩ/V	20 kΩ/V	5 kΩ/V	20 kΩ/V
otpor ~	5 kΩ/V	3 kΩ/V	5 kΩ/V	6,7 kΩ/V
Broj mernih dometa	31	32	27	24
Ohmski otpor Ω x	1,10,100, 1k,10k	1,10,100, 1k,10k	1,10,100 ♪	1,10,100
Pojačanje dB	∞	∞	-	∞
Indikacija polariteta	-	-	-	-
Redosled faza	-	-	-	-
Klasa tačnosti	2,5 ≡	2,5 ≡	1,5 = 2,5 ~	2,5 ≡
Značilnosti	-	-	Tonski davač	-
Napajanje	1x1,5V R6 1x15V 10F15	1x1,5V R6 1x15V 10F15	1 x1,5 V R6	1 x 1,5 V R6
Dimenzije (mm)	96 x132 x 33	96 x 132 x 33	96 x132 + 16 x 33	96 x 132 x 33

Pribor:

- Plastični etui za tipe MI 7042, ...43, ...45, ...46.
- Merne veze
- Zaštita od gume za tipe MI 7042, ...43, ...46.